

Vincent

PRODUCT INFORMATION

PHO-300

Phono Preamplifier

Are you looking for an affordable and excellent sounding device to operate your turntable on an amplifier with an ordinary line input? Then the new PHO-300 from the Vincent stable is exactly the right solution.

As with its big brothers, the PHO-701 and PHO-500, an elaborately designed external power supply unit is also used here. Negative effects on the part of the power supply, which can have a big influence on a phono preamplifier, are therefore a thing of the past. The power supply unit also keeps the power supply to the actual phono unit constant at all times - fluctuations from the public electricity network are thus unable to make any impact.



Vincent
German Brand since 1995

powerLine

PRODUCT INFORMATION

PHO-300

Phono Preamp

The phono unit has, of course, been equipped with selected components to ensure low-noise reproduction. It can be switched between moving magnet (MM) and moving coil (MC) and is therefore suitable for a wide range of sound pickups. The power supply unit and phono unit are built into high-quality aluminium housings and fit seamlessly into the PowerLine design.



Connections

SPECIFICATIONS

Frequency Response:	10 Hz – 20 kHz \pm 0.5 dB 10 Hz – 50 kHz \pm 2 dB
T.H.D.:	< 0.05% (20 Hz - 20 kHz)
Input Sensitivity:	MM: 58 mV, MC 6,8 mV
Signal-Noise Ratio:	MM: > 83 dB, MC: > 70 dB
Input Impedance:	MM: 47 kOhm, MC: 100 Ohm
Output Impedance:	250 Ohm
Amplification Factor:	MM: 40 dB, MC: 60 dB
Inputs:	PHO-300 1 x stereo RCA, 1 x 5-pin DIN (DC IN PHO-300)
Outputs:	PHO-300 1 x stereo RCA, 1 x 5-pin DIN (DC OUT PHO-300ps)
Max. Power Consumption:	10 Watt
Weight:	0,9 kg (PHO-300ps), 0,6 kg (PHO-300)
Color:	Black or Silver
Dimensions (W x H x D):	112 x 60 x 126 mm for power supply and PHO-300 each

Vincent
German Brand since 1995

powerLine

For further information, please contact Mr. Christian Fröhling.
Sintron Vertriebs GmbH, Südring 14, 76473 Iffezheim, Telephone: 07229-182950
e-mail: info@sintron.de, www.vincent-highend.de